



Commotion Control Box Computer Connection Wiring


The following diagrams and tables show how the connector cable is wired for the BBC microcomputer.



Control Box 25-way connector looking into the cable plug



BBC printer connector looking into the cable plug



BBC user port connector looking into the cable plug

Control Box Connector	BBC Connector
1	User - 14
2	User - 16
3	User - 18
4	User - 20
5	Printer - 3
6	Printer - 5
7	Printer - 7
8	Printer - 9
9	User - 1
14	User - 12
15	User - 10
16	User - 8
17	User - 6
18	Printer - 17
19	Printer - 15
20	Printer - 13
21	Printer - 11
23	Printer - 16

This is the standard wiring pattern for all Deltronics control boxes which connect to the User Port and Printer Port.